

List of CID events reports for JA 80Y

CID code	Event
1130/3130	Intruder alarm-instant/restored
1134/3134	Intruder alarm-delayed/restored
1110/3110	Fire alarm / restored
1120/3120	Panic alarm / restored
1461/3461	Number of incorrect entries exceeded alarm/restored
1140/3140	Alarm triggered during control panel power up /restored
1137/3137	Tamper alarm no tampering
1144/3144	Device tamper alarm /no tampering
1406	Alarm canceled by user
1401/3401	Unsetting /setting
3402	Partial setting
3408	Codeless complete settings
1354/3354	External communication fault/restored
1300/3300	Fault (except device)/all faults restored
1330/3330	Device fault/all faults restored
1301/3301	Main s dropout longer then 30 min/restored
1302/3302	Battery fault(except devices)/all batt. Fault restored
1384/3384	Device battery fault /all batt. Fault restored
1306/3306	Switching to service mode/Leaving service mode
1661/3661	PGX ON/OFF
1662/3662	PGY ON/OFF
1355	Radio communication jamming present
1350/3350	Internal communication fault/restored
1602	Communication test
1138	Unconfirmed alarm
1351	Communication fault to ARC 1 (to ARC 2 if backup)
1393	Annual check request
1551/3551	Communicator blocked/restored (only in IP cid)

List of source numbers

Source	Source number
Control panel	701
Communicator	731
Wired keypad	741
Devices 01-50	001-050
Master code	500
Service code	599
Codes 01-50	501-550

