

RC-40 Remote Control

The RC-40 combines two pairs of buttons (A&B and 1&2). It can be used to operate multiple wireless Jablotron devices. For example, one RC-40 can control your car alarm and your house alarm system or two independent partitions in a house alarm or up to 6 different devices when used with Jablotron UC receivers.

The RC-40 can send 6 instructions (A,B,1,2,A+B,1+2). It has a unique optional "keypad locking" feature (to prevent accidental activation or its unauthorized use). The RC-40 remote control is compatible with following Jablotron products:

- Wireless alarms: JA-6x (COMFORT, PROFI & MAESTRO)
- Universal receivers: UC-216, UC-222, UC-280 & UC-281
- Wireless wall switch: UC-230
- Wireless door bell & minialarm: UC-260
- Car alarms: CA-32x ACCENT and CA-10 REX
- Car central locking: CL-301 and CL-302



Locking the remote control keypad

To enable the locking feature unscrew and open the housing and remove the battery. Press the A button and while pressed reinsert the battery and keep holding the A button until the LED indicator flashes. Reassemble the remote control.

To lock keys, press simultaneously any two diagonal buttons (A+2 or B+1) until the LED indicator will flash. Now all buttons are locked. The LED indicator will rapidly blink if you press any button, but no signal will be transmitted.

To unlock the keys press any two diagonal buttons simultaneously (the same as locking).

To disable locking – perform enabling procedure (see above), disabling will be indicated by a flash of the LED.

Enrolling the RC-40 into a receiver

Read carefully the receiver's instructions. If a simultaneous pressing of A+B is requested to enroll the remote control (for example into a JA-6x control panel), you can use A+B and also 1+2. This way you can enroll the RC-40 as two different remote controls (right and left side buttons).

Battery replacement

When the battery is running low and the remote control working range gets shorter, replace it with a new one (type L1016).

Specifications

Power	6V battery (L1016 type)
Battery lifetime	typically 1 year
Frequency	433.92 MHz
Coding	digital floating security code
Keypad locking	optional feature
Can be operated according to ERC REC 70-03	
Complies with EN ETSI 300220, ETS 300683 and EN 50134.	



Pod Skalkou 33
466 01 Jablonec nad Nisou
Czech Republic
Tel.: +420 483 559 999
fax: +420 483 559 993
Internet: www.jablotron.cz

Hereby, Jablotron Ltd., declares that this RC-40 is in compliance with the essential requirements and other relevant provisions of Directive 1999/5/EC. Original of the conformity assessment can be found at the web page www.jablotron.cz, section Technical support.

Note: Dispose of batteries safely depending on the type of the batteries and local regulation. Although this product does not contain any harmful materials we suggest you to return the product to the dealer or directly to the producer after usage.