

JA-60 “Comfort” changes overview

There are several changes and improvements in the new version of the system JA-60 “Comfort”. The reason of the changes is to extend the current system and some of them are the result of communication with customers and installation companies.

The bellosed list pertains to the SW version FM 61211 compared to the version FM 61210.

Change	Programming sequence	Function	Reason	Note
Power supply check		In case of power failure of the control panel (battery or mains supply) the technology alarm is triggered, no matter what the status of the system is set (armed/disarmed)	User is warned of the limited function of the intruder system in any case	
Panic		The alarms of the particular sources are counted up to four, after this number the detector is ignored if the line of the four alarm event from this sensor has not been interrupted by any other source or by the system status change (arming/disarming). The panic alarms are not counted!	The source of the panic alarm, e.g. panic button, is not ignored after the fourth alarm event and the sources is able to transmit any other event.	
Delayed detector test	39X	During the arming process is the user's attention drawn to the active delayed or next delayed detectors	The function was extended for installation companies demand	
Programming mode	6999	Direct oversetting of the Programming mode to the User mode without the “N” key and master code entering	The set bypasses and theirs features are kept on	
Periphery enrolment	299	The enrolment sequence may be transmitted in the User mode as well	The user is allowed to enrol peripheries without the service code knowledge	Further information in the user manual
Timer	64 nahhmm	Possibility of the counter setting in the User mode	The user is allowed to set the automatic arming and disarming timer without the service code knowledge	