



## TD-110 Phone Dialer

The **TD-110** is an **auto-dialler** that plays a **prerecorded voice message** to **4 telephone numbers**. It can also send a **numeric message** to your **pager**.

### Descrizione

The dialer can be triggered manually or by another device connected to the TD-110 input. The dialer can automatically call for help or report different events. Its installation and programming is extremely easy compared to traditional dialers.

### Specifiche tecniche

<b>Operating Voltage</b>	10 - 14 VDC (adapter D01-12)
<b>Consumption</b>	Stand By max. 15 mA, Dialing max. 100 mA
<b>Triggering</b>	Connecting Or Disconnecting of IN1 With GND, Or Pressing Fce key
<b>Telephone Line</b>	Electrically Separated, Built In Over Voltage Protection
<b>Dialing Method</b>	Pulse or Tone (Factory Default = Tone)
<b>Tel. Num. memories</b>	4x 16 Digits for Voice Message Sending 1x 26 Digits for Pager Numeric Message Sending
<b>Voice Mess. Duration</b>	Max. 20sec., Record Is Repeated for 40sec. During Sending
<b>Number of Calls</b>	When Triggered, Each Programmed Number Is Called 3 times

**For Indoor Use Only, Working Temperature From -10 to +40°C.  
Complies With TBR-21 Standard.**