



TD-110 Phone Dialer

The **TD-110** is an **auto-dialler** that plays a **prerecorded voice message** to **4 telephone numbers**. It can also send a **numeric message** to your **pager**.

Descrição

The dialer can be triggered manually or by another device connected to the TD-110 input. The dialer can automatically call for help or report different events. Its installation and programming is extremely easy compared to traditional dialers.

Especificações técnicas

Operating Voltage	10 - 14 VDC (adapter D01-12)
Consumption	Stand By max. 15 mA, Dialing max. 100 mA
Triggering	Connecting Or Disconnecting of IN1 With GND, Or Pressing Fce key
Telephone Line	Electrically Separated, Built In Over Voltage Protection
Dialing Method	Pulse or Tone (Factory Default = Tone)
Tel. Num. memories	4x 16 Digits for Voice Message Sending 1x 26 Digits for Pager Numeric Message Sending
Voice Mess. Duration	Max. 20sec., Record Is Repeated for 40sec. During Sending
Number of Calls	When Triggered, Each Programmed Number Is Called 3 times

For Indoor Use Only, Working Temperature From -10 to +40°C.
Complies With TBR-21 Standard.